

MEGATRONICS 3.0 --> RepRapDiscount Full Graphic Smart Controller

LCD --> EXP1	KEYPAD --> EXP2 / EXP1	SD OUT --> EXP2
1 LCD (GND) --> 9 EXP1 (GND)	1 KEYPAD (5V/VCC) --> //	1 SD OUT (5V/VCC) --> //
2 LCD (5V/VCC) --> 10 EXP1 (VCC)	2 KEYPAD (GND) --> //	2 SD OUT (A2) --> ?
3 LCD (LCD contrast) --> //	3 KEYPAD (KEYPAD encoder) --> 5 EXP2 (BTN_EN1)	3 SD OUT (MISO) --> 1 EXP2 (PB3 (MISO))
4 LCD (LCD_RS) --> 4 EXP1 (LCDRS)	4 KEYPAD (KEYPAD D33) --> 2 EXP1 (BTN_EN0)	4 SD OUT (MOSI) --> 6 EXP2 (PB2 (MOSI))
5 LCD (GND) --> //	5 KEYPAD (KEYPAD encoder(2)) --> 3 EXP2 (BTN_EN2)	5 SD OUT (SCK) --> 2 EXP2 (PB1 (SCK))
6 LCD (LCD enable) --> 3 EXP1 (LCDE)	6 KEYPAD (KEYPAD shift out) --> //	6 SD OUT (SS) --> 4 EXP2 (SD_CSEL)
7 LCD (LCD 4) --> 5 EXP1 (LCD4)	7 KEYPAD (SHIFT clock) --> //	7 SD OUT (GND) --> //
8 LCD (LCD 5) --> 6 EXP1 (LCD5)	8 KEYPAD (SHIFT LD) --> //	8 SD OUT (not connected) --> //
9 LCD (LCD 6) --> 7 EXP1 (LCD6)		
10 LCD (LCD 7) --> 8 EXP1 (LCD7)		
11 LCD (5V) --> //		
12 LCD (GND) --> //		